

Enersound R-120 FM Receiver

FEATURES

- 20 Programmable Channels
- Compatible with most 72-76 Mhz FM systems
- Superb sound quality
- LCD screen with optional backlight (R-120BL only)
- On-screen low battery indicator
- On-screen volume indicator
- Feedback reduction feature
- Easy to use
- Easy access to the buttons
- Innovative and attractive design
- Multiple carrying options:
 - Belt clip
 - Neck strap
 - Velcro arm-band
- Utilizes 2 x 1.5V AAA batteries
- Low battery consumption (up to 35 working hr.)
- Small & lightweight
- Headphones included

A Service Oriented Company

Congress Network Corporation manufactures and distributes the best devices for simultaneous interpretation and assistive listening applications, providing a top quality customer service in English, Spanish and Portuguese.

Money back warranty!

More info in our Website



Picture of R-120BL



Enersound R-120 is an upgraded version of our popular Tango 20. This professional multichannel receiver has been exclusively developed for simultaneous interpretation purposes in the international market, as well as for multichannel assistive listening applications in the USA.

Its multiple features were designed to save time in this highly demanding business. In any conference or event with hundreds of receivers, there is no time to deal with interferences that may require several hours to reprogram each of the devices.

There is nothing like the simplicity of the Enersound R-120 receiver!

By pressing a single button you can switch frequencies that are strategically allocated. This increases your ability to overcome most of the difficulties that you may encounter in any event, in almost no time!

Technical Specifications

Number of channels: 20 programmable
Frequency range: FM 72.0 to 76.0 MHz
FM deviation: +/- 75 KHz
De-emphasis: 75 uS
Sensitivity: 1.413 uV at 12 db SINAD
Signal to noise ratio: 55 db at 100 uV
Audio frequency response: 70 Hz to 15kHz
Audio output power: 16 mW + 16mW at 16ohm
Audio Connector: 3.5mm stereo phone jack
Distortion: THD 0.5%
Current consumption: 27 mA nominal
Battery: 2xAAA (1.5V x 2)
Dimensions: 3" Diameter / 76 mm.
High: 1.22" / 31 mm.
Weight without batteries: 2.3 ounces / 65 grams
Weight with batteries: 3.1 ounces / 88 grams
Accessories included: Stereo headphone, arm band, neck strap, belt clip.

Specifications subject to change without notice.

Toll free: 1 800 757 2035 • Phone: 1 954 391 5007
customer@congressnetwork.com
Escribanos en español a consultas@CongressNetwork.com
Escreva-nos em português a brasil@CongressNetwork.com
www.CongressNetwork.com

